



Setting up a VISTA High End Panel for Total Connect 2.0

1. Required information to program the AlarmNet communicator:
 - a. City Number
 - b. CS Number
 - c. Account Number
 - d. Supervision level
 - e. MAC and CRC of the AlarmNet device
2. Log into AlarmNet 360
3. Go to the "Program New Device GSM/I" page
4. Enter the Account information and the Device information
5. Check the box "Enable Total Connect"
6. Select "Total Connect 2.0" from Dropdown box
7. Select "Advanced Programming"
8. If GSM device, the SIM will require activation
9. You will be redirected to the "Show Programmed Devices GSM/I" page
10. Set Keypad Address to any available unused address (Address needs to be set to keypad AUI type in the panel)
11. Set Multimode Address to any available unused address (Address needs to be set to RIS type in the Panel)
12. Click "Save and Transfer Data To Device" you will be redirected to the "Show Programmed Device" page
13. Update the page by clicking "Refresh List" button until the "Xfer(ET)" shows a down arrow with the correct date and time.
14. Ensure that the "Acct #" is highlighted in GREEN if not select "Register" under "Actions" and click the "GO" button
15. Repeat step 16 until the "Acct #" is highlighted GREEN
16. From the Action Dropdown select "Total Connect Setup" then click "GO"
17. Select "Total Connect 2.0" and click "NEXT"
18. Enter the "User Name" (Master User TC 2.0 Login Name)
19. Enter the "Account Name" (Account Name to identify the site)
20. Enter the "Email Address" (Email address of the Master User)
21. Select "Submit"

Additional Required Panel Programming (*93 Device Address Programming) to match what was selected in the AlarmNet Communicator

1. Address XX= Device Type 01 Alpha Console, AUI enabled (Keypad address)
2. Address XX = Device Type 06, Long Range Radio (Device ECP address)
3. Address XX = Device Type 12 RIS (Email Notification Address)