



**resideo**

## Setting up a VISTA Low End Panel for Total Connect 2.0

1. Required information to program the AlarmNet communicator:
  - a. City Number
  - b. CS Number
  - c. Account Number
  - d. Supervision level
  - e. MAC and CRC of the AlarmNet device
2. Log into AlarmNet 360
3. Go to the "Program New Device GSM/I" page
4. Enter the Account information and the Device information (a,b,c,d & e from step 1)
5. Check the box "Enable Total Connect"
6. Select "Total Connect 2.0" from Dropdown box
7. Select "Advanced Programming"
8. If GSM device, the SIM will require activation
9. You will be redirected to the "Show Programmed Devices GSM/I" page
10. Set Keypad Address to any available unused AUI address 1,2,5 or 6 (1,2 are on by default 5,6 need to be enabled in the panel)
11. Multimode Address must be set to 25
12. Click "Save and Transfer Data to Device" you will be redirected to the "Show Programmed Device" page
13. Update the page by clicking "Refresh List" button until the "Xfer(ET) shows a down arrow with the correct date and time.
14. Ensure that the "Acct #" is highlighted in GREEN if not select "Register" under "Actions" and click the "GO" button
15. Repeat step 16 until the "Acct #" is highlighted GREEN
16. From the Action Dropdown select "Total Connect Setup" then click "GO"
17. Select "Total Connect 2.0" and click 'NEXT'
18. Enter the "User Name" (Master User TC 2.0 Login Name)
19. Enter the "Account Name" (Account Name to identify the site)
20. Enter the "Email Address" (Email address of the Master User)
21. Select "Submit"

## Additional Required Panel Programming

1. Field \*29 needs to be set to 1 (Enables LRR Radio for ECP 3)
2. Field \*91 needs to be set to 8, 2 (Enables RIS for ECP 25)
3. If using ECP 5 or 6 for "keypad must set Field \*189 for 1,1